G

BAR CODE PRINTING ON PP20X

The PSi PP20x in the DL24C/DL24C+ emulation's supports 8 industrial standard Barcodes

Codabar, EAN 13, EAN 8, Code 3 of 9, 2 of 5 Industrial, 2 of 5 interleaved, Matrix 2 of 5, UPC Type A

Barcode sequence (header and Data)

ASCII ESC DC4 (b) R (c) (w) (h) (a) (ch1) (chn) Decimal 27 20 (b) 82 (c) (w) (h) (a) (ch1) (chn) HEX 1B 14 (b) 52 (c) (w) (h) (a) (ch1) (chn)

Where lower case letters are enclosed in parentheses, e.g. (b), they should be replaced with a single byte parameter as defined later.

note: The MSB of all parameters are ignored.

The command lenght varries defined by parameter (b)

Parameters (b) Byte Count

This specifies the number of subsequent bytes, including the byte count itself, in the command sequence e.g. if the data to be barcoded are 5 characters then (b) should be set to 11(decimal or 0B (HEX)

User's manual G-1

Parameters (c) Coding System

Barcode type

Parameter Value	Barcode Type
1 (31) HEX	Codabar
2 (32) HEX	EAN 13
3 (33) HEX	EAN 8
4 (34) HEX	Code 3 of 9
5 (35) HEX	2 of 5 industrial
6 (36) HEX	2 of 5 interleaved
7 (37) HEX	Matrix 2 of 5
A (41) HEX	UPC Type A

(w) Width of the narrow bars

This specifies the width of the narrow bars, in units of 1/1440 inch, the barcode will be printed in units of 1/180th inch

Parameter Value	Number of Dots
	180 dpi
0 to 19	2
20 to 27	3
28 to 127	4

(h) Height of bars

This specifies the height of the bars, in relation to the width of the narrow bars (w)

Height (h) is determined as follows: H=(h)/(w) units 1/1440 inch When (h) is less than 192 (24 dots at **240 dpi**), the barcode will be printed using a default (see following table)

Thin bar	EAN 13	EAN 8	Others
width			
2 dots	0.9 inch	0.7 inch	0.6 inch
3 dots	1.3 inch	1.0 inch	0.75 inch
4 dots	1.7 inch	1.4 inch	0.9 inch

G-2 Users manual

Parameters (a) Barcode Attributes

This parameter is used to define a byte which contains 8 binary flags. This byte switches the specific barcode attributes

Bit	Specification	Value	Meaning
Bit 0	Check Digit (*1)	0	added
		1	not added
Bit 1	OCR characters	0	printed
		1	not printed
Bit 2	Flag character	0	left of barcode
		1	lower left of barcode

^{*1} The check digit is always added for EAN and UPC barcodes. For Codabar no check digit is added (flag not needed).

(ch 1)....(ch n) Barcode Data

Definition of barcode range and type characters.

c Barcode type	Character set	range of data item (n)
Codabar	Numeric: 0-9	up to 34 character
	Signs: +,-,\$,/,:	including start/stop
	Start/Stop:A,a,B,b,C,c,D,d,	
	T,t,N,n,*,E,e	
EAN13	Numeric: 0-9	n = 12
EAN 8	Numeric: 0-9	n = 7
Code 39	Numeric: 0-9	up to 32 characters
	Alpha: A-Z	including check digit
	Special:+,-,%,\$,.,Space	
	Start/Stop:*	
2 of 5 industrial	Numeric: 0-9	as above
2 of 5 interleaved	Numeric: 0-9	as above
Matrix 2 of 5	Numeric: 0-9	as above
UPC Type A	Numeric: 0-9	n = 11

The data have to be set as ASCII characters corresponding to the character set used for each type of barcode. If they are not in a valid range, the command is canceled and the remaning data are skipped.

User's manual G-3

Barcode specifig restriction

Codarbar

The Start/Stop character is not checked by the printer. Barcode is printed based on the input data. The start/stop code must be set by the user. (Start/Stop codes: A,a,B,b,C,c,D,d,T,t,N,n,m,*,E,e) - both upper and lower characters can be used. OCR characters are printed in upper characters.

• Code 3 of 9

Only uppercase alpha characters can be used. The Start/Stop code (*) will be printed automatically as the first and last character in the output data string. Start/Stop code will be printed as OCR characters. Detection of the start/stop code in the input data causes an error.

2 of 5 interleaved

Barcode printing

The barcode requires an even number of the data code digits. In case of an odd number of digits, a "0" character precedes the input data. The start/stop code is placed automatically by the printer

 The barcode printing command is treated as a single vertically and horinzontally enlarged character by the printer in relation to other commands or characters, and can be positioned anywhere in the text

note: the barcode patterns are usally larger than standard text - for some barcode types exist restrictions

- If the barcode pattern is exceeding the defined right margin the barcode will not be printed
- The barcode pattern is printed from the current position even though the pattern may extend beyond the bottom margin
- The Flag character for EAN and UPC barcode is not printed if the barcode pattern is printed at the left margin without any previous spaces or characters.

G-4 Users manual

Barcode sample • Barcode sample EAN 13

this sample generates and outputs a barcode file "pp204.prn"

10 D\$ = ,,123456789012" printing data

20 CLEN = LEN (D\$) + 6 'total numbers of parameters
30 CODE\$ = ,2" 'barcode type EAN 13 (2)
40 BWIDTH = &H06 'width of barcode 6/1440 inch
50 BHEIGHT = &H60 'height of barcode 60/1440 inch

60 ATTRIB = &H1 'barcode attribute

65 OPEN "pp204.prn" FOR OUTPUT AS #1

70 PRINT #1, CHR\$(27); CHR\$(20); CHR\$(CLEN);

80 PRINT #1, ,,R";

90 PRINT #1, CODE\$;CHR\$(BWIDTH);CHR\$(BHEIGHT);

100 PRINT #1, CHR\$(ATTRIB);

110 PRINT #1, D\$;CHR\$(10);CHR\$(13);CHR\$(10);CHR\$(10);

120 PRINT #1, CHR\$(10); CHR\$(10);

130 PRINT #1, BARCODE TEST PRINTOUT PP204 EAN 13"

The result in the file "pp204.prn" is



User's manual G-5